


## Ultra LOW Capacitance ESD TVS Array

### Features

- 80Watts peak pulse power ( $t_p = 8/20\mu s$ )
- SOT23-6 package
- Solid-state silicon-avalanche technology
- Low clamping voltage
- Low leakage current
- Ultra low capacitance (0.2pF typical I/O to I/O)
- ESD Protection for high-speed data lines to:
  - IEC 61000-4-2  $\pm 15KV$  contact  $\pm 15KV$  air
  - IEC 61000-4-4 (EFT) 40A (5/50ns)
  - IEC 61000-4-5 (Lightning) 6A (8/20 $\mu s$ )
- RoHS compliant





Marking: .05L

SOT23-6

Schematic Diagram

### Applications

- USB 3.0, USB 2.0, MHL
- HDMI 2.0, Display Port 1.3, eSATA
- Unified Display Interface (UDI)
- Digital Visual Interface (DVI)
- High speed serial interfaces



### Absolute Maximum Ratings ( $T_A=25^\circ C$ , Unless otherwise specified.)

Parameter	Symbol	Value	Unit
Peak Pulse Power ( $T_p=8/20\mu S$ )	$P_{PP}$	80	W
Peak Pulse Current ( $t_p = 8/20\mu S$ )	$I_{PP}$	6	A
Junction Temperature	$T_J$	-55 to +125	$^\circ C$
Storage temperature	$T_{STG}$	-55 to +150	$^\circ C$


### Electrical Characteristics ( $T_A=25^\circ C$ , Unless otherwise specified.)

Parameter	Symbol	Condition	Min	Typ	Max	Unit
Reverse stand-off Voltage	$V_{RWM}$				5	V
Reverse Breakdown Voltage	$V_{BR}$	$I_T=1mA$	6	6.8	8.5	V
Reverse Leakage Current	$I_R$	$V_R=5V$		0.01	1	$\mu A$
Clamping Voltage(SURGE)	$V_C$	$I_{PP}=6A, T_p=8/20\mu S$		14	16	V
Trigger Voltage(ESD)	$V_T$	$V_{ESD} = +8kV$		90		V
Clamping Voltage(ESD)	$V_C$	$V_{ESD} = +8kV$		15		V
Junction Capacitance	$C_J$	$V_R=0V, f=1MHz, I/O$ to I/O		0.2	0.4	pF
	$C_J$	$V_R=0V, f=1MHz, I/O$ to GND		0.4	0.8	pF


## Ratings and Characteristics Curves

(TA = 25°C unless otherwise noted)


**Fig.1 Peak Pulse Power Rating Curve**




**Fig.2 Pulse Derating Curve**




**Fig.3 Pulse Waveform-8/20 $\mu s$**




**Fig.4 Pulse Waveform-ESD(IEC61000-4-2)**



**Fig.5 Eye Diagram - HDMI mask at 3.4Gbps per channel (with SESLC5VT236L-6U)**




**Fig.6 Insertion Loss S21 - I/O to GND**




## Package Outline Dimensions

in inches (millimeters)



Symbol	Dimensions in millimeters		Dimensions in inches	
	Min	Max	Min	Max
A	1.050	1.250	0.041	0.049
A1	0.000	0.100	0.000	0.004
A2	1.050	1.150	0.041	0.045
b	0.300	0.500	0.012	0.020
c	0.100	0.200	0.004	0.008
D	2.820	3.020	0.111	0.119
E1	1.500	1.700	0.059	0.067
E	2.650	2.950	0.104	0.116
e	0.950(BSC)		0.037(BSC)	
e1	1.800	2.000	0.071	0.079
L	0.300	0.600	0.012	0.024
θ	0°	8°	0°	8°

## Part Number System



## Revision History

Document Version	Date of release	Discription of changes
Rev.A	2014.03.25	First issue

## **Disclaimers**

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd. or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page.

(<http://www.goodark.com>)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.